

Esc 1BH 1BH 1BH 1BH 1BH	F1 F1H F1H EEH, F1H F1H F1H	F2 F2H F2H EEH, F2H F2H F2H	F3 F3H F3H EEH, F3H F3H F3H	F4 F4H F4H EEH, F4H F4H F4H	F5 F5H F5H EEH, F5H F5H F5H	F6 F6H F6H EEH, F6H F6H F6H	F7 F7H F7H EEH, F7H F7H F7H	F8 F8H F8H EEH, F8H F8H F8H	F9 F9H F9H EEH, F9H F9H F9H	F10 FAH FAH EEH, FAH FAH FAH	F11 FBH FBH EEH, FBH FBH FBH	F12 FCH FCH EEH, FCH FCH FCH	PRNT SCRN C6H C6H EEH, C6H C6H C6H	SCRL LOCK C7H C7H EEH, C7H C7H C7H	PAUSE C8H C8H EEH, C8H C8H C8H						
` 60H 7EH EEH, 60H 00H 60H	1 31H 21H EEH, 31H 31H 31H	2 32H 40H EEH, 32H 32H 32H	3 33H 23H EEH, 33H 33H 33H	4 34H 24H EEH, 34H 34H 34H	5 35H 25H EEH, 35H 35H 35H	6 36H 5EH EEH, 36H 36H 36H	7 37H 26H EEH, 37H 37H 37H	8 38H 2AH EEH, 38H 38H 38H	9 39H 28H EEH, 39H 39H 39H	0 30H 29H EEH, 30H 30H 30H	- 2DH 5FH EEH, 2DH 2DH 2DH	= 3DH 2BH EEH, 3DH 3DH 3DH	\ 5CH 7CH EEH, 5CH 5CH 5CH	BK SPC 08H 08H EEH, 08H 08H 08H	INSERT C0H C0H C0H C0H C0H	HOME C1H C1H C1H C1H C1H	PGUP C2H C2H C2H C2H C2H	NUM LOCK NO CODES	/ 2FH 2FH 2FH 2FH	* 2AH 2AH 2AH 2AH	- 2DH 2DH 2DH 2DH
TAB 09H 09H 09H 09H 09H	Q 71H 51H EEH, 71H 11H 71H	W 77H 57H EEH, 77H 17H 77H	E 65H 45H EEH, 65H 05H 65H	R 72H 52H EEH, 72H 12H 72H	T 74H 54H EEH, 74H 14H 74H	Y 79H 59H EEH, 79H 19H 79H	U 75H 55H EEH, 75H 15H 75H	I 69H 49H EEH, 69H 09H 69H	O 6FH 4FH EEH, 6FH 0FH 6FH	P 70H 50H EEH, 70H 10H 70H	[ 5BH 7BH EEH, 5BH 1BH 5BH	] 5DH 7DH EEH, 5DH 1DH 5DH	ENTER 0DH 0DH 0DH 0DH 0DH	DELETE C3H C3H C3H C3H C3H	END C4H C4H C4H C4H C4H	PGDN C5H C5H C5H C5H C5H	7-HOME D7H D7H EEH, D7H D7H 37H	8-UP D8H D8H EEH, D8H D8H 38H	9-PGUP D9H D9H EEH, D9H D9H 39H	+2BH 2BH 2BH 2BH 2BH	
CAPS LOCK NO OUTPUT, MODIFIES CODES ONLY	A 61H 41H EEH, 61H 01H 61H	S 73H 53H CONFIG 13H 73H	D 64H 44H EEH, 64H 06H 64H	F 66H 46H EEH, 66H 06H 66H	G 67H 47H EEH, 67H 07H 67H	H 68H 48H EEH, 68H 08H 68H	J 6AH 4AH EEH, 6AH 0AH 6AH	K 6BH 4BH EEH, 6BH 0BH 6BH	L 6CH 4CH EEH, 6CH 0CH 6CH	; 3BH 3AH EEH, 3BH 1BH 3BH	' 27H 22H EEH, 27H 07H 27H						4-LEFT D4H D4H EEH, D4H D4H 34H	5 D5H D5H EEH, D5H D5H 35H	6-RIGHT D6H D6H EEH, D6H D6H 36H		
SHIFT NO OUTPUT, MODIFIES CODES ONLY	Z 7AH 5AH EEH, 7AH 1AH 7AH	X 78H 58H EEH, 78H 18H 78H	C 63H 43H EEH, 63H 03H 63H	V 76H 56H EEH, 76H 16H 76H	B 62H 42H EEH, 62H 02H 62H	N 6EH 4EH EEH, 6EH 0EH 6EH	M 6DH 4DH EEH, 6DH 0DH 6DH	, 2CH 3CH EEH, 2CH 0CH 2CH	. 2EH 3EH EEH, 2EH 0EH 2EH	/ 2FH 3FH EEH, 2FH 0FH 2FH	SHIFT NO OUTPUT, MODIFIES CODES ONLY			UP ARROW DAH DAH EEH, DAH DAH DAH			1-END D1H D1H EEH, D1H D1H 31H	2-DN D2H D2H EEH, D2H D2H 32H	3-PGDN D3H D3H EEH, D3H D3H 33H	ENTER 0DH 0DH 0DH 0DH 0DH	
CTRL NO OUTPUT, MODIFIES CODES ONLY	ALT NO OUTPUT, MODIFIES CODES ONLY			SPACE 20H 20H 20H 20H 20H				ALT NO OUTPUT, MODIFIES CODES ONLY		CTRL NO OUTPUT, MODIFIES CODES ONLY			LEFT ARROW DBH DBH EEH, DBH DBH DBH	DOWN ARROW DCH DCH EEH, DCH DCH DCH	RIGHT ARROW DDH DDH EEH, DDH DDH DDH		0-INSERT D0H D0H EEH, D0H D0H 30H	.-DEL DEH DEH EEH, DEH DEH 2EH			

Order of precedence for control keys:

- 1) ALT key(s)
- 2) Control Key(s)
- 3) NumLock
- 4) SHIFT key(s)

Key Legend

Normal Key Value
Shifted Key Value
ALT Key Value
Control Key Value
NumLock Key Value

Title <b>PS2PROX KEY MAP</b>		
Size B	Document Number {Doc}	Rev -
Date: Friday, March 16, 2018	Sheet 1	of 1